



Drive MCDHT3520

URL:https://www.sxplc.com/drive-mcdht3520

Product data sheet

| Item | | Specifications |
|----------------------------------|---|--|
| Part Number | | MCDHT3520 |
| Details | | A5 series |
| | Speed, Position, Torque, Full-closed type | |
| | w | ith the safety function |
| Family Name | | MINAS A5 |
| Series | | A5 series |
| Туре | Speed, Pos | sition, Torque, Full-closed type |
| Frame | | C-Frame |
| Frequency response (kHz) | | 2.3 |
| Control method | Position control, Veloc | ity control, Torque control, and Full-closed |
| | | control |
| Safety Function | | with |
| Power device Max. current rating | | 30A |
| Current detector current rating | | 20A |
| Supply voltage | S | Single/3-phase 200 V |
| I/F Classification of type | | Analog/Pulse |
| Dimensions (W) (Unit: mm) | | 65 |
| Dimensions (H) (Unit: mm) | | 150 |
| | | |

| Dimensions (D) (Unit: mm) | 170 |
|---------------------------|---|
| Mass (kg) | 1.6 |
| Environment | For more details, please refer to the instruction manual. |

Basic Specifications

| Item | | Specifications |
|-------------------------------|-------------------------|--|
| Input power: Main circuit | Single/3-phase 200 V (| (+10% -15%) to 240 V (+10% -15%) 50/60 |
| | | Hz |
| Input power: Control circuit | Single phase 200 V (+1 | 0% -15%) to 240 V (+10% -15%) 50/60 Hz |
| Encoder feedback | 17-bit (131072 reso | plution) absolute encoder, 7-wire serial |
| | 20-bit (1048576 resol | lution) incremental encoder, 5-wire serial |
| External scale feedback | A/B phase, homing sig | nal differential input. Serial communication |
| | | is also supported. |
| Parallel I/O connector: | Ger | neral purpose 10 inputs |
| Control signal Input | The function of genera | I-purpose input is selected by parameters. |
| Parallel I/O connector: | Ge | neral purpose 6 output |
| Control signal Output | The function of general | -purpose output is selected by parameters. |
| Parallel I/O connector: | 3 inputs (16-bit | A/D : 1 input, 12-bit A/D : 2 inputs) |
| Analog signal Input | | |
| Parallel I/O connector: | 2 output | s (Analog monitor: 2 output) |
| Analog signal Output | | |
| Parallel I/O connector: | 2 inputs (Photo | -coupler input, Line receiver input) |
| Pulse signal Input | | |
| Parallel I/O connector: | 4 outputs (Line driv | ver: 3 output, open collector: 1 output) |
| Pulse signal Output | | |
| Communication function | L | JSB, RS232, RS485 |
| Communication function: USB | USB interface to conn | ect to computers for parameter setting or |
| | | status monitoring. |
| Communication function: RS232 | | 1:1 communication |

| Communication function: RS485 | 1: n communication (max 31) | |
|-------------------------------|---|--|
| Regeneration | Built-in regenerative resistor (external resistor is also enabled.) | |
| Control mode | Switching among the following 7 mode is enabled, | |
| | (1) Position control, (2) Speed control, (3) Torque control, (4) | |
| | Position/speed control, (5) Position/Torque control, (6) | |
| | Speed/Torque control, (7) Full-closed control | |

