



## Inverter FR-E840-0026-4-60

URL: <https://www.sxplc.com/inverter-fr-e840-0026-4-60>

### Product data sheet

Series	FR-E800 SERIES
Type	FR-E800 RS485 INVERTER
Minimum Rated Voltage (V)	380
Min. Permissible Voltage (V)	323
Maximum Rated Voltage (V)	480
Max. Permissible Voltage (V)	528
Current Type	AC
Phases	3
Rated Output Current LD (A)	3,5
Rated Output Current ND (A)	2,6
Rated Motor Capacity LD (kW)	1,5
Rated Motor Capacity ND (kW)	0,75
Control Method	V/F CONTROL, REAL SENSORLESS VECTOR CONTROL, PM SENSORLESS VECTOR CONTROL, MAGNETIC FLUX VECTOR CONTROL
Motor Type	INDUCTION MOTOR, PM MOTOR
Brake Chopper ED (%)	100
Integrated EMC Filter	NO
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	BUILT-IN
Display Type	4 DIGITS LED
PLC Function	YES
Program Memory	2K
Program Memory Unit	STEPS
Integrated Digital Inputs	7
Digital Outputs (Transistor)	2
Digital Outputs (Relay)	1
Integrated Analogue Inputs	2
Integrated Analogue Outputs	1
IO Type of Terminal Block	SPRING CLAMP
Expandable	YES
RS-485	1
USB	1 (MINI B)
Ethernet Port	NO
Built-In Network	MODBUS-RTU
Leakage Current (mA)	1,2
Power Loss LD (W)	55
Power Loss ND (W)	38
Frequency Range (Hz)	0,2–590
Protection Class	IP20

## Product Dimensions & Weight

Width (mm)	108
Height (mm)	128
Depth (mm)	129,5
Weight (kg)	1,2

## Conformity

