



Rotary Encoder E6C2-CWZ6C

URL: <https://www.sxplc.com/rotary-encoder-e6c2-cwz6c>

Product data sheet

Categorise	Incremental Shaft model
Diameter	50 mm dia.

Power supply voltage	5 to 24 VDC (-5% to +15%) Ripple (p-p) 5% max.
Current consumption	80 mA max.
Resolution	1000 P/R
Inrush current	Approx. 9 A (0.3 ms)

Output phases	A, B and Z	
Control output	Output type	NPN open collector
	Load power supply voltage	30 V max.DC

	Sink current	35 mA max.
	Residual voltage	0.4 V max. (at sink current 35 mA)

