



## **Inductive sensor**

**IFT203IFB3004BBPKG/V4A/US-104**

URL:<https://www.sxplc.com/inductive-sensor-ift203ifb3004bbpkg-v4a-us-104>

**Product data sheet**

<b>Operating voltage [V]</b>	10...30 DC
<b>Protection class</b>	II
<b>Reverse polarity protection</b>	yes

## Outputs

<b>Electrical design</b>	PNP/NPN
<b>Output function</b>	normally open
<b>Max. voltage drop switching output DC [V]</b>	2.5
<b>Minimum load current [mA]</b>	2
<b>Max. leakage current [mA]</b>	0.5
<b>Permanent current rating of switching output DC [mA]</b>	100
<b>Switching frequency DC [Hz]</b>	250
<b>Short-circuit protection</b>	yes
<b>Type of short-circuit protection</b>	pulsed
<b>Overload protection</b>	yes

