



Inductive sensor IB5065

IB-3020-BPKG/10M

URL:<https://www.sxplc.com/inductive-sensor-ib5065-ib-3020-bpkg-10m>

Product data sheet

Operating voltage [V]	10...36 DC
Current consumption [mA]	15; (24 V)
Protection class	II
Reverse polarity protection	yes

Outputs

Electrical design	PNP
Output function	normally open
Max. voltage drop switching output DC [V]	2.5
Permanent current rating of switching output DC [mA]	250
Switching frequency DC [Hz]	60
Short-circuit protection	yes
Type of short-circuit protection	pulsed
Overload protection	yes

