



Inductive sensor IB5065

IB-3020-BPKG/10M

URL:<https://www.sxplc.com/inductive-sensor-ib5065-ib-3020-bpkg-10m>

Product data sheet

| | |
|------------------------------------|------------|
| Operating voltage [V] | 10...36 DC |
| Current consumption [mA] | 15; (24 V) |
| Protection class | II |
| Reverse polarity protection | yes |

Outputs

| | |
|---|---------------|
| Electrical design | PNP |
| Output function | normally open |
| Max. voltage drop switching output DC [V] | 2.5 |
| Permanent current rating of switching output DC [mA] | 250 |
| Switching frequency DC [Hz] | 60 |
| Short-circuit protection | yes |
| Type of short-circuit protection | pulsed |
| Overload protection | yes |

